








| General | ▶ DVJ-X1 | ▶ CDJ-1000 MK3 | ▶ CDJ-1000 MK2 | ▶ CDJ-800 MK2 | ▶ CDJ-200 | ▶ CDJ-100S | ▶ DMP-555 |
|----------------------------|---|---|---|---|---|---|---|
| Short description | Pro DVD Video Deck | Digital CD Deck | Digital CD Deck | Digital CD Deck | Digital CD Deck with MP3 | CD Deck | Digital Media Player |
| Image |  |  |  |  |  |  |  |
| Key features | ▶ DVJ-X1 DVD Video & Audio Mixing | ▶ CDJ-1000 MK3 | ▶ CDJ-1000 MK2 | ▶ CDJ-800 MK2 | ▶ CDJ-200 | ▶ CDJ-100S | ▶ DMP-555 |
| Performance Control | ▶ DVJ-X1 | ▶ CDJ-1000 MK3 | ▶ CDJ-1000 MK2 | ▶ CDJ-800 MK2 | ▶ CDJ-200 | ▶ CDJ-100S | ▶ DMP-555 |
| Hot Cue (sampler) | Yes | Yes | Yes | | | | |
| Hot Loop | | Yes | Yes | | Yes | | |
| Quick Start | Yes | Yes | Yes | Yes | Yes | Yes | Yes |
| Auto Beat Loop / Emergency | Yes | | | | Yes | | |
| Beat / Loop Cutter | | | | | Yes | | |
| Quick Return | | | | Yes | | | |
| Reverse | Yes | Yes | Yes | Yes | | | |
| Real Time Seamless Loop | Yes | Yes | Yes | Yes | Yes | | Yes |
| Loop Adjust | Out Adjust | In / out Adjust | In / out Adjust | Out Adjust | Out Adjust | | out adjust |
| Reloop | Yes | Yes | Yes | Yes | Yes | | Yes |
| Digital Jog Break | | | | | Jet, Zip & Wah | Jet, Zip & Wah | |
| Memory | ▶ DVJ-X1 | ▶ CDJ-1000 MK3 | ▶ CDJ-1000 MK2 | ▶ CDJ-800 MK2 | ▶ CDJ-200 | ▶ CDJ-100S | ▶ DMP-555 |
| MMC-Multimediacard | Yes | Yes | Yes | | | | Yes |
| Memory | Internal & Removable SD Card | Internal & Removable MMC (Multimedia Card) | Internal & Removable MMC (Multimedia Card) | | | | |
| Wave Data | Yes | Yes | Yes | | | | |
| Cue / Loop Memory | Yes | Yes | Yes | Yes | Yes | | |
| Shock-Proof | Yes | Yes | Yes | Yes | Yes | Yes | Yes |
| CD Control | ▶ DVJ-X1 | ▶ CDJ-1000 MK3 | ▶ CDJ-1000 MK2 | ▶ CDJ-800 MK2 | ▶ CDJ-200 | ▶ CDJ-100S | ▶ DMP-555 |
| Jog Dial size | 206,0 mm | 206,0 mm | 206,0 mm | 206,0 mm | 100,0 mm | 100,0 mm | 100,0 mm |
| Jog Dial type | Touch sensitive | Touch sensitive | Touch sensitive with silver JOG Ring | Touch sensitive | Jog Dial | Sensitive Jog Dial | |
| Jog Modes | CDJ / Vinyl Mode | CDJ / Vinyl Mode | CDJ / Vinyl Mode | CDJ / Vinyl Mode | CDJ mode | CDJ mode | |
| Pitch Bend | Yes | Yes | Yes | Yes | Yes | Yes | Yes |
| Scratch Play / Cue | Yes | Yes | Yes | Yes | | | Yes |
| Quick Scratch | After searching Track After Hot Cue REC After Hot Cue Play | After searching Track | After searching Track After Hot Cue REC After Hot Cue PLAY | After searching Track | | | |

| | | | | | | | |
|------------------------------|--|--|--|--|--|--------------------|-----------------------------------|
| Fader Start / Back Cue start | Yes | Yes | Yes | Yes | Yes | Yes | Yes |
| Relay Play | Yes | Yes | Yes | Yes | Yes | Yes | Yes |
| Frame Search | | 1/75 Sec | 1/75 Sec | | 1/75 Sec | | |
| Vinyl Speed Adjust | Yes | Yes | Yes | Yes | | | |
| Tempo | ▶ DVJ-X1 | ▶ CDJ-1000 MK3 | ▶ CDJ-1000 MK2 | ▶ CDJ-800 MK2 | ▶ CDJ-200 | ▶ CDJ-100S | ▶ DMP-555 |
| Master Tempo | Yes | Yes | Yes | Yes | Yes | Yes | Yes |
| Tempo Control steps | 0.02% at +/-6%, 0.05% at +/-10% & 16% | | 0.02% at +/-6%, 0.05% at +/-10% & 16% | | 0.02% at +/-6%, 0.05 at +/- 10% & 16% | 0.1% at +/-10% | |
| Tempo Control Ranges (CD) | +/-6%, +/-10%, +/- 16%, +/-100% | | +/-6%, +/-10%, +/- 16%, +/-100% | | +/- 6%, +/- 10%, +/- 16% | +/-10% or +10/-16% | +/- 6%, +/- 10%, +/- 16% |
| Tempo Control Ranges (DVD) | +/-6%, +/-10%, +/- 16%, +70% -100% | | | | | | |
| BPM Counter | Yes | Yes | Yes | Yes | Yes | | Yes |
| Front loading Slot-In CD | Yes | Yes | Yes | Yes | Yes | Yes | Yes |
| Cue Functions | ▶ DVJ-X1 | ▶ CDJ-1000 MK3 | ▶ CDJ-1000 MK2 | ▶ CDJ-800 MK2 | ▶ CDJ-200 | ▶ CDJ-100S | ▶ DMP-555 |
| Auto Cue | Yes | Yes | Yes | Yes | Yes | Yes | Yes |
| Manual Cue | Yes | Yes | Yes | Yes | Yes | Yes | Yes |
| Real Time Cue | Yes | Yes | Yes | Yes | Yes | Yes | Yes |
| Cue point sampler | Yes | Yes | Yes | | Yes | Yes | Yes |
| Display | ▶ DVJ-X1 | ▶ CDJ-1000 MK3 | ▶ CDJ-1000 MK2 | ▶ CDJ-800 MK2 | ▶ CDJ-200 | ▶ CDJ-100S | ▶ DMP-555 |
| Display | Bright Display with Red Cue point on JOG Display | | Bright Display with Red Cue point on JOG Display | | Yes | Yes | CD Text + large screen display |
| Wave Display | Yes | Yes | Yes | | | | |
| Jog Display | Yes | Yes | Yes | Yes | | | |
| Playing Address | Yes | Yes | Yes | Yes | Yes | Yes | Yes |
| General | ▶ DVJ-X1 | ▶ CDJ-1000 MK3 | ▶ CDJ-1000 MK2 | ▶ CDJ-800 MK2 | ▶ CDJ-200 | ▶ CDJ-100S | ▶ DMP-555 |
| Media Loading Type | Slot | Slot | Slot | Slot | Slot | Slot | |
| Legato Link Conversion | Yes | | Yes | | | | Yes |
| Headphone Output | | | | | Yes | | |
| Anti Vibration | Yes | Yes | Yes | Yes | Yes | Yes | Yes |
| Analogue Output | 1 stereo RCA | 1 stereo RCA | 1 stereo RCA | 1 stereo RCA | Yes | 1 stereo RCA | 2x |
| Digital Output | Yes | Yes | Yes | Yes | Yes | | Yes |
| Type of Discs | 12cm DVDs / CDs | 12 & 8cm CDs | 12 & 8cm CDs | 12 & 8cm CDs | 12 & 8cm CDs | | |
| Disc Format | DVD, DVD-R, DVD-RW CD, CD-R, CD-RW | CD, CD-R, CD-RW, MP3 CD | CD, CD-R & CD-RW | CD, CD-R, CD-RW, MP3 CD | CD, CD-R, CD-RW, MP3 CD | CD, CD-R | |
| MP3 | | MPEG-1 32Kbps - 320 Kbps / MPEG-2 16 Kbps - 160 Kbps | | MPEG-1 32Kbps - 320 Kbps / MPEG-2 16 Kbps - 160 Kbps | MPEG-1 32Kbps - 320 Kbps / MPEG-2 16 Kbps - 160 Kbps | | |

| | | | | | | | |
|-----------------------------------|---|--|---|---|--|---|---------------------------|
| MP3 Folder Search | | Yes | | Yes | Yes | | |
| Included Accessories | 32 MB SD MMC (Movable Memory Card), power cord, manual, stereo phone cable, RCA video cable, Forced Eject Pin | MMC (Movable memory card), power cord, manual, stereo phono cable, Control Cable, Forced Eject Pin | MMC (Movable memory card), power cord, manual, stereo phono cable, Forced Eject Pin | Power cord, manual, stereo phono cable, Control Cable, Forced Eject Pin | Power cord, manual, stereo phono cable, Control Cord, Forced Eject Pin | Powercord, stereo phono cable, forced eject pin, manual | DJ Booth software |
| Master Video Output | ▶ DVJ-X1 | ▶ CDJ-1000 MK3 | ▶ CDJ-1000 MK2 | ▶ CDJ-800 MK2 | ▶ CDJ-200 | ▶ CDJ-100S | ▶ DMP-555 |
| Composite Out (2) | <ul style="list-style-type: none"> ● Output Level: 1 Vp-p (75 Ohm) ● Output Connector Sets: RCA (1), BNC (1) | | | | | | |
| S Video Out | <ul style="list-style-type: none"> ● Y Output Level: 1 Vp-p (75 Ohm) ● C Output Level: 286m Vp-p (75 Ohm) ● Output Connector: S Type (4 pin DIN) | | | | | | |
| Component Video Out | <ul style="list-style-type: none"> ● Y Output Level: 1 VP-p (75 Ohm) ● CB/PB, CR/PR: 0.7 Vp-p (75 Ohm) ● Output Connector: BNC Type | | | | | | |
| Preview Video Output | ▶ DVJ-X1 | ▶ CDJ-1000 MK3 | ▶ CDJ-1000 MK2 | ▶ CDJ-800 MK2 | ▶ CDJ-200 | ▶ CDJ-100S | ▶ DMP-555 |
| Composite Out | <ul style="list-style-type: none"> ● Output Level: 1 Vp-p (75 Ohm) ● Output Connector Sets: RCA | | | | | | |
| S Video Out | <ul style="list-style-type: none"> ● Y Output Level: 1 Vp-p (75 Ohm) ● C Output Level: 286m Vp-p (75 Ohm) ● Output Connector: S Type (4 pin DIN) | | | | | | |
| Specifications | ▶ DVJ-X1 | ▶ CDJ-1000 MK3 | ▶ CDJ-1000 MK2 | ▶ CDJ-800 MK2 | ▶ CDJ-200 | ▶ CDJ-100S | ▶ DMP-555 |
| Frequency Response | 4 Hz ~ 20 kHz | 4 Hz ~ 20 kHz | 4 Hz ~ 20 kHz | 4 Hz ~ 20 kHz | 4 Hz ~ 20 kHz | 4 Hz ~ 20 kHz | |
| Frequency Response (DVD [96 kHz]) | 4 Hz ~ 44 kHz | | | | | | |
| Signal to Noise Ratio | 115 dB or more (EIAJ) | 115 dB or more (JEITA) | 115 dB or more (EIAJ) | 115 dB or more (JEITA) | 110 dB or more (EIAJ) | 96 dB or more (EIAJ) | |
| Distortion | (T.H.D) 0.006% (EIAJ) | 0,006 % (JEITA) | 0,006 % (EIAJ) | 0,006 % (JEITA) | 0.006% (EIAJ) | | |
| Audio Output Level | 2.0 V rms (1kHz, 0 dB) | | 2 V | | 2 V | | |
| Power Consumption | 47 W | 27 W | 31 W | 24 W | 16 W | | |
| Power Requirements | 220 - 240 V, 50/60 Hz | | 220 - 240 V, 50/60 Hz | | 220 - 240 V, 50/60 Hz | | 220 - 240 V, 50/60 Hz |
| Dimensions (W x H xD) | 348 x 128 x 451 mm | 320 x 105 x 370 mm | 320 x 105 x 370 mm | 305 x 108.5 x 144.1 mm | 216 x 292 x 99.5 mm | 217 x 91 x 297 mm | |
| Net Weight | 7.3 kg | 4.2 kg | 4.2 kg | 4 kg | 3.2 kg | 2.2 kg | |

